



TravelMate Spin B1

























Battery Life





Product views	 Webcam 11.6" display Headset/speaker jack USB 3.0 port 	 HDMI[®] port Ethernet (RJ-45) DC-in jack 	port	8. Touchpad 9. Keyboard 10. Power key	 11. SD™ card reader 12. USB port 13. Kensington lock slot
Operating system ^{1, 2}	Windows 10 Pro-64-bit				
CPU and chipset ¹	Intel® Pentium [™] Silver N5000 processor Intel® Celeron® quad-core processor N4100 Intel® Celeron® qual-core processor N4000				
Memory ^{1, 3, 4, 5}	Dual-channel DDR4 SDRAM support 4 GB of onboard DDR4 system me 8 GB of onboard DDR4 system me	emory			
Display ⁶	11.6" display with IPS (In-Plane Switching) technology, Full HD 1920 x 1080, high-brightness, LED-backlit TFT LCD with integrated multi-touch • 16:9 aspect ratio • Wide viewing angle • Mercury free, environment friendly			11.6" display with IPS (In-Plane Switching) technology, HD 1366 x 768, high- brightness, LEO-backlit TFT LCD with integrated 10-finger touch ● 16:9 aspect ratio ● Wide viewing angle ● Mercury free, environment friendly	
Graphics	Intel® UHD Graphics 605 Intel® UHD Graphics 600				
Audio	Two built-in stereo speakers Built-in microphone				
Storage ^{1, 7,}	Hard disk drive Solid state drive ● 500 GB, 2.5-inch 5400 RPM ● 128 GB, SATA 6 Gb/s		eMMC ● 64 / 32 GB		
Webcam ¹	HD camera with ■ 1280 x 720 resolution ■ 720p HD audio/video recording				
Wireless and networking ¹	WLAN ■ Intel® Dual Band Wireless-AC, 802.11ac/a/b/g/n wireless LAN with Acer Nplify TM , featuring 2x2 MIMO technology		WPAN ● Bluetooth® 4.0 ● Bluetooth® 2.1+EDR		
Security	 Trusted Platform Module (TPM) s BIOS user, supervisor, HDD passw Kensington lock slot 				
Dimensions and weight ^{1, 8, 9}	Dimensions ● 291 (W) x 211(D) x 22.3 (H) mm (1	1.46 x 8.31 x 0.88inches)		Weight ● 1.59 kg (3.51 lbs.) with 4-cell battery	y pack
Power adapter and battery ^{1, 10}	Power adapter ■ 3-pin 45 W AC adapter		Battery ■ 48 Wh 3220 mAh 15.2 V 4-cell Li-ion battery pack ■ Battery life up to 13 hours		
Input and control	Keyboard 83-/84-/87-key Acer FineTip keybo Control Keys Power button	ard with international langua	ge support		
Windows Desktop Apps ¹¹	Acer ControlCenterAcer Product Registration	Quick AccessAcer Collection		 Acer Configuration Manager 	
System compliance ¹²	ENERGY STAR®Wi-Fi®EPEAT® register				
Warranty	One-year International Travelers Wa				
Quality and reliability tests	 Temperature and humidity Hinge life Weight and pressure 	AcousticsSpillageFree drop		 Shock and vibration Electrostatic discharge immunity Keyboard-switch life 	 MTBF (mean time between failures)
Shared system memory m other factors. Actual syste used by the graphics solut Memory speed may vary, c. A 64-bit operating system All brands and product na are used solely to describe 16B is 1 billion bytes, 1 TE	It to enjoy the advantages of 64-bit processing ay be allocated to support graphics, dependim m memory available to the operating system ion and resources required by the operating et lepending on the CPU, chipset or memory fitte is required to enjoy the ultimate performance mes mentioned herein include trademarks of or identify the products. is 1000 GB. Actual formatted capacity is less perating environment. Acer Recovery Manage perating environment.	g on system memory size and will be reduced by any memory nvironment. td. co f 4 GB or higher memory. heir respective companies and and may vary depending on	selected 9. Minor va 10. Listed ba MobileM only. Act condition 11. Bundled	nay vary depending on product configuration, ven options. riations in system dimensions are possible due to tattery life is based on MobileMark 2014 "productired are 2014" esting are available at www.bapco.cor ual battery life varies by model, configuration, ap 180, and features used. A battery's maximum capac software may vary depending on hardware configuration varies by country. See http://www.epegstration varies by country. See http://www.epe	the manufacturing process. vity mode testing with wireless on. Details of n. Battery life rating is for comparison purposes plication, power management settings, operating ity decreases with time and use. juration, OS and regional availability.

In a continuing effort to improve the quality of our products, information in this document is subject to change without notice. Images shown are only representations of some of the configurations available for this model. Availability may

In a continuing effort to improve the quality of our products, information in this document is subject to change without notice. Images snown are only representations of some of the configurations available for this model. Availability may vary depending on region.

As a phenomenon known to thin-film transistors (TFTs), liquid crystal displays (LCDs) commonly exhibit a small number of discoloration dots, as so-called "non-conforming pixels." This phenomenon is a limitation of TFT LCD technology, not a product defect, and as such is not covered by Acer's warranty.

© 2018. All rights reserved.

Microsoft and Windows are registered trademarks of Microsoft Corporation.

Intel and the Intel logo are trademarks of Intel Corporation or its subsidiaries in the U.S. and/or other countries.

About Acer